

Model – PAG700

### Switch Settings

<b>DAB700 Switch Settings</b>			
Switch No.	Function	ON	OFF
1,2	Gate Open Speed - Slow	-	S1,S2
1,2	Gate Open Speed - Med. Slow	S1	S2
1,2	Gate Open Speed - Med. Fast	S2	S1
1,2	Gate Open Speed - Fast	S1,S2	-
3,4	Gate Close Speed - Slow	-	S3,S4
3,4	Gate Close Speed - Med. Slow	S3	S4
3,4	Gate Close Speed - Med. Fast	S4	S3
3,4	Gate Close Speed - Fast	S3,S4	-
5	Gate Motor Direction	CCW	CW
6	Input Test Enable	ON	OFF
7	Motor Type	HOGAN	Velocity
8	Brake Mode in Open Position	ON	OFF
9	Brake Mode in Closed Position	ON	OFF
10	Fire Alarm Direction	B	A
11	Open Trigger Memory	ON	OFF
12,13	Auto Close Timer – 8 Sec	-	S12,S13
12,13	Auto Close Timer – 10 Sec	S12	S13
12,13	Auto Close Timer – 15 Sec	S13	S12
12,13	Auto Close Timer – 30 Sec	S12,S13	-
14,15	Close Delay – 0 Sec	-	S14,S15
14,15	Close Delay – 2 Sec	S14	S15
14,15	Close Delay – 4 Sec	S15	S14
14,15	Close Delay – 6 Sec	S14,S15	-
16	Operation Buzzer	ON	OFF
17	Spare	-	-
18	Trigger Hold Open	ON	OFF
19	LEARN MODE – Switch ON for 5 seconds	ON	OFF
20	Test Mode – 2 Second Auto Cycle	ON	OFF